

### 800-1000 MHz

#### Features:




- Cavity Linear Aluminum Board Design
- Quadrature Input for High Power Signal Combining
- 800-1000 MHz, Compatible of CDMA / GSM900
- Very Small Insertion Loss and High Isolation
- Good Amplitude and Phase Accuracy
- Continuous Wave Handling Power of 250W
- Good Price-Performance Ratio and Quick Delivery

#### Technical Specifications:

Frequency	800 – 1000 MHz
Insertion loss	3 ± 0.3 dB
Input VSWR	1.2
Output VSWR	1.2
Isolation	25 dB
Amplitude Balance	± 0.3 dB
Phase Balance	2°
Forward power	250 W

#### Order Information:

CMIPC-101 All N Female Connector  
Please contact manufacturer for all other requirements.




**CALL OUR SALES DEPARTMENT FOR MORE INFORMATION OR VARIATIONS OF THIS PRODUCT.**

**Corry Micronics, Inc. One Plastics Rd. - Corry, PA 16407**  
**(814) 664-7728 Fax (814) 664-4582 [www.cormic.com](http://www.cormic.com)**

Corry Micronics Inc. herein referred to CMI, believes this information to be accurate, but makes no warranties, expressed or implied as to the accuracy of this document. CMI assumes no liability for any injury, loss, damage, direct or consequential arising from the use of our products. User assumes all risk whatsoever in connection with it's intended use. CMI also reserves the right to change this document without notice.

**Notes:**

In is the input port; out is the output port;  
Terminator port connecting with 50Ω load.



**CALL OUR SALES DEPARTMENT FOR MORE INFORMATION OR VARIATIONS OF THIS PRODUCT.**

**Corry Micronics, Inc. One Plastics Rd. - Corry, PA 16407  
(814) 664-7728 Fax (814) 664-4582 [www.cormic.com](http://www.cormic.com)**

Corry Micronics Inc. herein referred to CMI, believes this information to be accurate, but makes no warranties, expressed or implied as to the accuracy of this document. CMI assumes no liability for any injury, loss, damage, direct or consequential arising from the use of our products. User assumes all risk whatsoever in connection with it's intended use. CMI also reserves the right to change this document without notice.